

Bypass (Dimmer) [55]

Bypass for dimmer light switch

Compatibility	LightSwitch (Dimmer) Jeweller The bypass is also compatible with third-party dimmers. Carefully read the manufacturer's instructions for third-party dimmer, before connecting Bypass (Dimmer) [55].
Installation	Connection in parallel with the lighting appliance The device can be installed in a lamp junction box.
Recommendations	The device is designed for indoor use only. A professional electrician should install the device.
Power supply	Voltage 230 V, 50 Hz The device is connected in parallel with the lighting appliance. Average consumption up to 1 W
Product	Enclosure dimensions 31 × 24 × 11 mm 1.22" × 0.94" × 0.43" Wires length 90 ± 5 mm 3.54" ± 0.02" Weight 7 g 0.25 oz Operating temperature range from -10 °C to +40 °C from 14 °F to 104 °F Operating humidity up to 75% with no condensation Form factor of the compatible dimmer European type (55)
Complete set	Bypass (Dimmer) [55] Quick start guide
Warranty	24 months